



[Cliquez ici pour découvrir ce produit en 360°](#)

INFORMATIONS PRODUIT



Référence : GB-150-011



Protocoles : 2 fils



Technologies : 868MHz, MIFARE® Plus

DESCRIPTION

Easy Door Receiver is a HF access control system designed for small-scale residential structures. This product is a controller and a receiver. It is designed for 2 doors and can manage up to 2,000 users.

This product can be used remotely from the location it is installed in (this is known as Virtual Network mode) or on site (standalone mode).

For remote management, you only need an Internet connection to the website:
www.easydoorcontroller.com and our USB encoder.

Next:

1. Note the number of the controller installed (specified on the cover)
2. Register on www.easydoorcontroller.com
3. Programme the keys/passes using the encoder that records one or several doors that can be accessed inside the key/pass/remote control.

To delete permissions for a key/pass/remote control remotely, you just need to cancel this key/pass on the website and programme a new one instead. When the new key/pass is used for the first time, the old one is immediately blocked.

KEY CHARACTERISTICS

- Size (L X H X P) : 120 mm x 100 mm x 40 mm
- Remote programming with an encoder and an Internet connection
- Wiring: 2 wires / 100 m max. between the reader and the controller.
- Power supply: 12/24 Vac or Vcc
- NO/NC relay switch
- Time delay adjustable from 1 second to 99 seconds
- Pluggable terminals
- Operating temperature: -20°C to +60°C